



LED Emergency

TL-RMES003

"Running Man" LED Emergency Combo Sign





Features & Benefits

Injection-molded thermoplastic housing

Easy installation

Ni-cd battery backup for 90 minutes

Universal (wall, ceiling) mounting

2W x 2 SMD LED adjustable heads

120/347VAC input voltage

3 Pictograms included, single/ double face

cUL listed / IP20


Test switch and charge indicator light

Warranty

5-year limited warranty in commercial use from the date of purchase $% \left\{ 1,2,...,n\right\}$

Operating temperature range between 0°C and +40°C

Dimensional Drawing







Ordering Information Example: TL-RMES003

Fan	Family Name Fixture Type		Model		
TL	Turolight) RMES ("Running Man" Emergency Sign)		003 (Emergency Combo Sign)		

Product Specification

Ordering Code	Model Number	Description	Wattage (W)	Input Volt- age (V)	Mounting	Self Powered Battery	Damp Location	Dimensions L×W×H (inch)	Case QTY.
3461210	TL-RMES003	"Running Man" LED Emergency Sign, White Housing AC only	3W	120/347VAC	wall, ceiling	Yes (90 minutes)	Yes	13.0 ×8.5 ×2.4	6