



# LED Emergency TL-RMES101

"Running Man" LED Emergency Sign





#### **Features & Benefits**

Injection-molded thermoplastic housing

Easy installation

Ni-cd battery backup for 90 minutes

Universal (wall, ceiling) mounting

SMD LED

120/347VAC input voltage

3 Pictograms included, single/ double face

cUL listed / IP20


Test switch and charge indicator light

#### Warranty

5-year limited warranty in commercial use from the date of purchase

Operating temperature range between 0°C and +40°C

## **Dimensional Drawing**







## Ordering Information Example: TL-RMES003

Family Name Fixture Type		Model				
TL (Turolight)	RMES ("Running Man" Emergency Sign)	101 (Emergency Sign )				

### **Product Specification**

Ordering Code	Model Number	Description	Wattage (W)	Input Volt- age (V)	Mounting	Remote Capable	Self Powered Battery	Damp Location	Dimensions L×W×H (inch)	Case QTY.
3461114	TL-RMES101	"Running Man" LED Emergency Sign, White Housing AC only	3W	120/347VAC	wall, ceiling	No	Yes (90 minutes)	Yes	13.0 ×8.5 ×2.4	6