



LED Emergency TL-RMES003, RMES302

"Running Man" LED Emergency Combo Sign







Features & Benefits

Injection-molded thermoplastic housing (RMES003). RMES302 metal housing c/w 36W 6V battery pack, allows for the addition of Remote heads.

Easy installation

Ni-cd battery backup for 90 minutes

Universal (Wall, Ceiling) mounting

2W x 2 super bright SMD LED adjustable heads

120/347VAC input voltage

3 Pictograms included, single/ double face

cUL listed / IP20


Test switch and charge indicator light

Warranty


 $\ensuremath{\text{2-year}}$ limited warranty in commercial use from the date of purchase

Operating temperature range between -10°C and +40°C

Dimensional Drawing







Ordering Information Example: TI-RMES003

Family Name	Fixture Type	Model			
TL (Turolight)	RMES ("Running Man" Emergency Sign)	003 ("Running Man" Combo Sign) Plastic			
		302 ("Running Man" Combo Sign) Metal, additional 6VDC remote head capable			





Product Specification

1 Todate Specification												
Ordering Code	Model Number	Description	lmage	Wattage (W)	Input Voltage (V)	Mounting	Self Powered Battery	Damp Location	Dimensions L×W×H (inch)	Case QTY.		
3461210	TL-RMES003	"Running Man" LED Emergency Sign, White Plastic Housing	₹	4W	120/347VAC	Wall, Ceiling	Yes (90 minutes)	Yes	13.0″×12.2″×4″	4		
3461212	TL-RMES302	"Running Man" LED Emergency Sign, White Metal Housing	☆ →	36W	120/347VAC	Wall, Ceiling	Yes (90 minutes)	Yes	12.2"×11.02"×2.13"	6		