



# LED Emergency

TL-RMES101

"Running Man" LED Emergency Sign







#### **Features & Benefits**

Injection-molded thermoplastic housing

Easy installation

Ni-cd battery backup for 90 minutes, AC only & 6-24V UDC (TL-RMES101-UDC)

Universal (Wall, Ceiling, Side) mounting

Super bright SMD LED

120/347VAC input voltage

3 Pictograms included, single/ double face

cUL listed / IP20


Test switch and charge indicator light

#### Warranty

2-year limited warranty in commercial use from the date of purchase

Operating temperature range between -10°C and +40°C

## **Dimensional Drawing**







## Ordering Information Example: TL-RMES101

Family Name	Fixture Type	Model				
TL (Turolight)	RMES ("Running Man" Emergency Sign)	101 (Emergency Sign ) 101-UDC (Emergency Sign, AC only & 6-24V UDC)				

### **Product Specification**

Ordering Code	Model Number	Description	Wattage (W)	Input Volt- age (V)	Mounting	Remote Capable	Self Powered Battery	Damp Location	Dimensions L×W×H (inch)	Case QTY.
3461114	TL-RMES101	"Running Man" LED Emergency Sign, White Housing	3W	120/347VAC	Wall, Ceiling, Side	No	Yes (90 minutes)	Yes	13.0"×8.5"×2.4"	6
3461116	TL-RMES101-UDC	"Running Man" LED Emergency Sign, White Housing AC only & 6-24V UDC	3W	120/347VAC	Wall, Ceiling, Side	Yes	NO	Yes	13.0"×8.5"×2.4"	6