



LED Emergency

TL-RMES301

"Running Man" LED emergency sign in metal







Features & Benefits

CRS housing + PC panel(s)

Easy installation

Ni-cd battery backup for 2 hrs (TL-RMES301) AC only & 6-24V UDC (TL-RMES301-UDC)

Universal (wall, ceiling, side) mounting

Super bright SMD LED

3 Pictograms included, single/ double face

CSA C22.2 No. 141/ IP20


Test switch and charge indicator light

Warranty

2-year limited warranty in commercial use from the date of purchase

Operating temperature range between -10°C and +40°C

Dimensional Drawing







Ordering Information Example: TI-RMES301

1	Family Name	Fixture Type	Model				
	TL (Turolight)	RMES ("Running Man" Emergency Sign)	301 (Emergency Sign)				
			301D-UDC (Emergency Sign AC only & 6-24V UDC)				

Product Specification

Ordering Code	Model Number	Description	Wattage (W)	Input Volt- age (V)	Mounting	Remote Capable	Self Powered Battery	Damp Location	Dimensions L×W×H (inch)	Case QTY.
3481100	TL-RMES301	"Running Man" LED Emergency Sign, White Metal Housing Ni-cd battery backup for 2 hours	3W (120V) 4W (347V)	120/347VAC	Wall, Ceiling, Side	No	Yes (2 hrs)	Yes	12.2"×7.5"×2.2"	10
3461118	TL-RMES301-UDC	"Running Man" LED Emergency Sign, White Metal Housing AC only & 6-24V UDC	3W (120V)	120/347VAC	Wall, Ceiling, Side	Yes	No	Yes	12.2"×7.5"×2.2"	10